

# On the Optimality of WLAN Location Determination Systems

Moustafa A. Youssef, Ashok Agrawala  
Department of Computer Science and UMIACS  
University of Maryland  
College Park, Maryland 20742  
{moustafa, agrawala}@cs.umd.edu  
UMIACS-TR-2003-29 and CS-TR-4459  
March 11, 2003

## Abstract

*This report presents a general analysis for the performance of WLAN location determination systems. In particular, we present an analytical method for calculating the average distance error and probability of error of WLAN location determination systems. These expressions are obtained with no assumptions regarding the distribution of signal strength or the probability of the user being at a specific location, which is usually taken to be a uniform distribution over all the possible locations in current WLAN location determination systems. We use these expressions to find the optimal strategy to estimate the user location and to prove formally that probabilistic techniques give more accuracy than deterministic techniques, which has been taken for granted without proof for a long time. The analytical results are validated through simulation experiments. We also study the effect of the assumption that the user position follows a uniform distribution over the set of possible locations on the accuracy of WLAN location determination systems. The results show that knowing the probability distribution of the user position can reduce the number of access points required to obtain a given accuracy. However, with a high density of access points, the performance of a WLAN location determination system is consistent under different probability distributions for the user position.*

## 1. Introduction

WLAN location determination systems use the popular 802.11 [10] network infrastructure to determine the user location without using any extra hardware. This makes these systems attractive in indoor environments where traditional techniques, such as the Global Positioning System (GPS) [5], fail to work or require specialized hardware. Many applications have been built on top of location determination systems to support pervasive computing. This includes [4] location-sensitive content delivery, direction finding, asset tracking, and emergency notification.

In order to estimate the user location, a system needs to measure a quantity that is a function of distance. Moreover, the system needs one or more reference points to measure the distance from. In case of the GPS system, the reference points are the satellites and the measured quantity is the time of arrival of the satellite signal to the GPS receiver, which is directly proportional to the distance between the satellite and the GPS receiver. In case of WLAN location determination systems, the reference points are the access points and the measured quantity is the signal strength, which decays logarithmically with distance in free space. Unfortunately, in indoor environments, the wireless channel is very noisy and the radio frequency (RF) signal can suffer from reflection, diffraction, and multipath effect [9, 11], which makes the signal strength a complex function of distance. To

overcome this problem, WLAN location determination systems tabulate this function by sampling it at selected locations in the area of interest. This tabulation has been known in literature as the radio map, which captures the signature of each access point at certain points in the area of interest.

WLAN location determination systems usually work in two phases: offline phase and location determination phase. During the offline phase, the system constructs the radio-map. In the location determination phase, the vector of samples received from each access point (each entry is a sample from one access point) is compared to the radio-map and the “nearest” match is returned as the estimated user location. Different WLAN location determination techniques differ in the way they construct the radio map and in the algorithm they use to compare a received signal strength vector to the stored radio map in the location determination phase.

In this report, we present a *general* analysis of the performance of WLAN location determination systems. In particular, we present a general analytical expression for the average distance error and probability of error of WLAN location determination systems. These expressions are obtained with *no assumptions regarding the distribution of signal strength or user movement profile*. We use these expressions to find the *optimal* strategy to use during the location determination phase to estimate the user location. These expressions also help to prove *formally* that probabilistic techniques give more accuracy than deterministic techniques, which has been taken for granted without proof for a long time. We validate our analysis through simulation experiments. We also present an analysis of the effect of the assumption that the user location is uniformly distributed over the set of all possible locations on the performance of the location determination systems. For the rest of the report we will refer to the probability distribution of the user location as the *user profile*.

To the best of our knowledge, our work is the first to analyze the performance of WLAN location systems analytically, provide the optimal strategy to select the user location, and study the effect of the user profile on the performance of WLAN location determination systems.

The rest of this report is structured as follows. Section 2 summarizes the previous work in the area of WLAN location determination systems. Section 3 presents the analytical analysis for the performance of the WLAN location determination systems. In Section 4, we validate our analytical analysis through simulation and provide experiments to test the effect of the user profile on the performance of location determination systems. Section 5 concludes the report and presents some ideas for future work.

## 2. Related Work

Radio map-based techniques can be categorized into two broad categories: deterministic techniques and probabilistic techniques. *Deterministic techniques* (such as [2, 8]) represent the signal strength of an access point at a location by a scalar value, for example, the mean value, and use non-probabilistic approaches to estimate the user location. For example, in the *Radar* system [2] the authors use nearest neighborhood techniques to infer the user location. On the other hand, *probabilistic techniques* (such as [3, 7, 6, 12]) store information about the signal strength distributions from the access points in the radio map and use probabilistic techniques to estimate the user location. For example, the *Horus* system from the University of Maryland [12, 13] uses the stored radio map to find the location that has the maximum probability given the received signal strength vector.

All these systems base their performance evaluation on experimental testbeds which may not give a good idea on the performance of the algorithm in different environments. The authors in [7, 12, 13] showed that their probabilistic technique outperformed the deterministic technique of the *Radar* system [2] in a *specific* testbed and conjectured that probabilistic techniques should outperform deterministic techniques. This report presents a general *analytical* method for analyzing the performance of different techniques. We use this analysis method to provide a formal proof that probabilistic techniques outperform deterministic techniques. Moreover, we show the optimal strategy for selecting locations in the location determination phase.

All the current WLAN location determination systems assume that the user has an equal probability for being at any location in the set of radio map locations (uniform user profile). We study the effect of this uniform user

profile assumption on the performance of the location determination systems.

### 3. Analytical Analysis

In this section, we give an analytical method to analyze the performance of WLAN location determination techniques. We start by describing the notations used throughout the report. We provide two expressions: one for calculating the average distance error of a given technique and the other for calculating the probability of error (i.e. the probability that the location technique will give an incorrect estimate).

#### 3.1. Notations

We consider an area of interest whose radio map contains  $N$  locations. We denote the set of locations as  $\mathbb{L}$ . At each location, we can get the signal strength from  $k$  access points. We denote the  $k$ -dimensional signal strength space as  $\mathbb{S}$ . Each element in this space is a  $k$ -dimensional vector whose entries represent the signal strength reading from different access points<sup>1</sup>. Since the signal strength returned from the wireless cards are typically integer values, the signal strength space  $\mathbb{S}$  is a discrete space. For a vector  $s \in \mathbb{S}$ ,  $f_{\mathcal{A}}^*(s)$  represents the estimated location returned by the WLAN location determination technique  $\mathcal{A}$  when supplied with the input  $s$ . For example, in the *Horus* system [12, 13],  $f_{\text{Horus}}^*(s)$  will return the location  $l \in \mathbb{L}$  that maximizes  $P(l/s)$ . Finally, we use  $\text{Euclidean}(l_1, l_2)$  to denote the Euclidean distance between two locations  $l_1$  and  $l_2$ .

#### 3.2. Average Distance Error

We want to find the average distance error (denoted by  $E(\text{DErr})$ ). Using conditional probability, this can be written as:

$$E(\text{DErr}) = \sum_{l \in \mathbb{L}} \{E(\text{DErr}/l \text{ is the correct user location}).P(l \text{ is the correct user location})\} \quad (1)$$

where  $P(l \text{ is the correct user location})$  depends on the user profile.

We now proceed to calculate  $E(\text{DErr}/l \text{ is the correct user location})$ . Using conditional probability again:

$$\begin{aligned} & E(\text{DErr}/l \text{ is the correct user location}) \\ &= \sum_{s \in \mathbb{S}} \{E(\text{DErr}/s, l \text{ is the correct user location}).P(s/l \text{ is the correct user location})\} \\ &= \sum_{s \in \mathbb{S}} \{\text{Euclidean}(f_{\mathcal{A}}^*(s), l).P(s/l \text{ is the correct user location})\} \end{aligned} \quad (2)$$

where  $\text{Euclidean}(f_{\mathcal{A}}^*(s), l)$  represents the Euclidean distance between the estimated location and the correct location.

Equation 2 says that to get the expected distance error given we are at location  $l$ , we need to get the weighted sum, over all the possible signal strength values  $s \in \mathbb{S}$ , of the Euclidean distance between the estimated user location ( $f_{\mathcal{A}}^*(s)$ ) and the actual location  $l$ .

Substituting equation 2 in equation 1 we get:

$$E(\text{DErr}) = \sum_{s \in \mathbb{S}} \sum_{l \in \mathbb{L}} \{\text{Euclidean}(f_{\mathcal{A}}^*(s), l).P(s/l \text{ is the correct user location}).P(l \text{ is the correct user location})\} \quad (3)$$

Note that the effect of the location determination technique is summarized in the function  $f_{\mathcal{A}}^*$ . We seek to find the function that minimizes the probability of error. We defer the optimality analysis till we present the *probability of error* analysis.

---

<sup>1</sup>if an access point cannot be heard at a given location, this is represented by a special signal strength value.

### 3.3. Probability of Error

In this section, we want to find an expression for the probability of error which is the probability that the location determination technique will return an incorrect estimate. This can be obtained from equation 3 by noting that every non-zero distance error (represented by the function  $\text{Euclidean}(f_{\mathcal{A}}^*(s), l)$ ) is considered an error. More formally, we define the function:

$$g(x) = \begin{cases} 0 & : x = 0 \\ 1 & : x > 0 \end{cases}$$

The probability of error can be calculated from equation 3 as:

$$P(\text{Error}) = \sum_{s \in \mathbb{S}} \sum_{l \in \mathbb{L}} \{g(\text{Euclidean}(f_{\mathcal{A}}^*(s), l)) \cdot P(s/l \text{ is the correct user location}) \cdot P(l \text{ is the correct user location})\} \quad (4)$$

In the next section, we will present a property of the term  $g(\text{Euclidean}(f_{\mathcal{A}}^*(s), l))$  and use this property to get the optimal strategy for selecting the location.

### 3.4. Optimality

We will base our optimality analysis on the probability of error.

**Lemma 1** *For a given signal strength vector  $s$ ,  $g(\text{Euclidean}(f_{\mathcal{A}}^*(s), l))$  will be zero for only one location  $l \in \mathbb{L}$  and one for the remaining  $N - 1$  locations.*

**Proof** For a given signal strength vector  $s$ , the location determination technique will return a single location. If this location matches the correct location  $l$ , the distance error will be zero and hence the function  $g$ . If not, the distance error will be greater than zero and the function  $g$  will equals one. The estimated location  $f_{\mathcal{A}}^*(s)$  can only match one of the possible  $N$  locations.  $\square$


The lemma states that only one location will give a value of zero for the function  $g(\text{Euclidean}(f_{\mathcal{A}}^*(s), l))$  in the inner sum. This means that the optimal strategy should select this location in order to minimize the probability of error. This leads us to the following theorem.

**Theorem 1 (Optimal Strategy)** *Selecting the location  $l$  that maximizes the probability  $P(s/l) \cdot P(l)$  is both a necessary and sufficient condition to minimize the probability of error.*

**Proof [Sufficient part]** Selecting the location that maximizes the probability  $P(s/l) \cdot P(l)$  will lead to making the function  $g$  in the inner sum equals zero for this probability. Since this technique removes the maximum probability for all  $s \in \mathbb{S}$ , this minimizes the overall probability of error.

**[Necessary part]** By contradiction: Assume not, then there exist an optimal strategy  $\mathcal{A}_1$  that for at least one signal strength vector  $s$ , selects a location  $l'$  that does not maximize the product  $P(s/l') \cdot P(l')$ . Let the probability of error using this strategy be  $E1$ . Consider another strategy  $\mathcal{A}_2$  that take the same decisions as  $\mathcal{A}_1$  except for the signal strength vector  $s$ , where it returns the location  $l$  that maximizes the product  $P(s/l) \cdot P(l)$ . Let the probability of error using this strategy be  $E2$ . Clearly,  $E2$  is less than  $E1$  which contradicts our assumption that  $\mathcal{A}_1$  is optimal.  $\square$

Theorem 1 suggests that the optimal location determination technique should store in the radio map the signal strength distributions to be able to calculate  $P(s/l)$ . Moreover, the optimal technique needs to know the user profile in order to calculate  $P(l)$ .



**Figure 1. Expected error for the special case of two locations**

**Corollary 1** *Deterministic techniques are not optimal.*

**Proof** Since deterministic techniques do not store any information about the signal strength distribution at each location, it follows from Theorem 1 that they are not optimal.  $\square$

Note that we did not make any assumption about the independence of access points, user profile, or signal strength distribution in order to get the optimal strategy.

A major assumption by *all* the current WLAN location determination systems is that all user locations are equi-probable. In this case,  $P(l) = \frac{1}{N}$  and Theorem 1 can be rewritten as:

**Theorem 2** *If the user is equally probable to be at any location of the radio map locations  $\mathbb{L}$ , then selecting the location  $l$  that maximizes the probability  $P(s/l)$  is both a necessary and sufficient condition to minimize the probability of error.*

**Proof** The proof is a special case of the proof of Theorem 1.  $\square$

This means that, for this special case, it is sufficient for the optimal technique to store the histogram of signal strength at each location. This is exactly the technique used in the *Horus* system [12, 13].

Figure 1 shows a simplified example illustrating the intuition behind the analytical expressions and the theorems. In the example, we assume that there are only two locations in the radio map and that at each location only one access point can be heard whose signal strength, for simplicity of illustration, follows a continuous distribution. The user can be at any one of the two locations with equal probability. For the *Horus* system (Figure 1.a), consider the line that passes by the point of intersection of the two curves. Since for a given signal strength the technique selects the location that has the maximum probability, the error if the user is at location 1 is the area of curve 1 to the right of this line. If the user is at location 2, the error is the area of curve 2 to the left of this line. The expected error probability is half the sum of these two areas as the two locations are equi-probable. This is the same as half the area under the minimum of the two curves (shaded in figure).




Figure 2. Plan of the floor where the experiment was conducted. Readings were collected in the corridors (shown in gray).

For the *Radar* system (Figure 1.b), consider the line that bisects the signal strength space between the two distribution averages. Since for a given signal strength the technique selects the location whose average signal strength is closer to the signal strength value, the error if the user is at location 1 is the area under curve 1 to the right of this line. If the user is at location 2, the error is the area under curve 2 to the left of this line. The expected error probability is half the sum of these two areas as the two locations are equi-probable (half the shaded area in the figure).

From Figure 1, we can see that the *Horus* system outperforms the *Radar* system since the expected error for the former is less than the later (by the hashed area in Figure 1.b). The two systems would have the same expected error if the line bisecting the signal strength space of the two averages passes by the intersection point of the two curves. This is not true in general. This has been proved formally in the above theorems.

We provide simulation and experimental results to validate our results in Section 4.

### 3.5. Averaging Signal Strength Vectors

Different WLAN location determination systems [13, 7] suggested that averaging multiple signal strength vectors and using the averaged vector as an input to the system enhances the system performance. In this section, we extend our analysis to cover the case of averaging of multiple signal strength vectors.

We start by obtaining the distribution of the average vector. Let  $X$  be the random variable (R.V.) representing the average of  $n$  signal strength vectors ( $s_i$ 's) at a given location, all coming from the same distribution (denoted by  $P(s/l)$ ). Consider the random variable  $Y = \sum_{i=1}^n s_i$ , the distribution of the R.V.  $Y$  is the  $n$  times convolution of the original distribution ( $P(s/l)$ ). Since  $X = Y/n$ , this implies that  $P(X = x) = P(Y = n.x)$ . This relates the distribution of the R.V.  $X$  to the original signal strength distribution  $P(s/l)$ .

To obtain the average distance error and probability of error, we can use equations 3 and 4 and substitutes the distribution of the R.V.  $X$  instead of the original signal strength distributions. The equation for the average

distance error (Equation 3) becomes:

$$E(\text{DErr}) = \sum_{s' \in \mathcal{S}'} \sum_{l \in \mathcal{L}} \{\text{Euclidean}(f_{\mathcal{A}}^*(s'), l) \cdot P(X = s'/l \text{ is the correct user location}) \cdot P(l \text{ is the correct user location})\} \quad (5)$$

Where  $\mathcal{S}'$  is the new signal strength space for the R.V.  $X$  representing the average of  $n$  signal strength vectors.

The equation for the probability of error (Equation 4) becomes:

$$P(\text{Error}) = \sum_{s' \in \mathcal{S}'} \sum_{l \in \mathcal{L}} \{g(\text{Euclidean}(f_{\mathcal{A}}^*(s'), l)) \cdot P(X = s'/l \text{ is the correct user location}) \cdot P(l \text{ is the correct user location})\} \quad (6)$$

The effect of averaging multiple signal strength vectors is to reduce the variance of the resulting distribution and hence reduce the overlap between distributions. The less the overlap, the better the error. Note that Theorems 1 and 2 still hold for averaging multiple signal strength vectors.

## 4. Simulation Experiments

In this section, we validate our analytical results through simulation experiments. For this purpose, we chose to implement the *Radar* system [2] from Microsoft as a deterministic technique and the *Horus* system [12, 13] from the University of Maryland as a probabilistic technique that satisfy the optimality criteria as described in Theorem 2. We start by describing the experimental testbed that we use to validate our analytical results and evaluate the systems.

### 4.1. Testbed

We performed our experiment in a floor covering an 20,000 feet area. The layout of the floor is shown in Figure 2. Both techniques were tested in the Computer Science Department wireless network. The entire wing is covered by 12 access points installed in the third and fourth floors of the building.

For building the radio map, we took the radio map locations on the corridors on a grid with cells placed 5 feet apart (the corridor's width is 5 feet). We have a total of 110 locations along the corridors. On the average, each location is covered by 4 access points.

We used the *mwvlan* driver and the *MAPI* API [1] to collect the samples from the access points.

### 4.2. Simulator

We built a simulator that takes as an input the following parameters:

- the radio map locations coordinates.
- the signal strength distributions at each location from each access point.
- the distribution over the radio map locations that represents the steady state probability of the user being at each location (*user profile*).
- $n$ : the number of signal strength vectors to average.

The simulator then chooses a location based on the user location distribution and generates a signal strength vector according to the signal strength distributions at this location. The simulator feeds the generated signal strength vector to the location determination technique. The estimated location is compared to the generated location to determine the distance error.

The next section analyze the effect of the user profile on the performance of the location determination systems. We validate our analytical results in all the experiments.

### 4.3. Effect of User Profile on Performance

We made three experiments that differ in how heterogeneous is the user profile:

- *Profile 1*: The user has equal probability of being at any location (uniform user profile).
- *Profile 2*: The user can be in one of two groups of locations. The probability of being in one group is twice the probability of being in the second group. The user has equal probability of being at any location within a group.
- *Profile 3*: The user has an exponentially damping distribution for being at different radio map locations. More specifically, the probability of being at location  $i$  is given by:

$$P(\text{Location} = i) = \begin{cases} \left(\frac{1}{2}\right)^i & : 1 < i < N - 1 \\ \left(\frac{1}{2}\right)^{N-1} & : i = N \end{cases}$$

The heterogeneity of the user profile increases as we move from profile one to profile three. The purpose of these simulation experiments is to study the effect of the assumption that the user location follows a uniform distribution over all possible locations on the performance of the location determination systems. The next subsections show the results of these experiments.

#### 4.3.1. Uniform user location distribution

This is similar to the assumption taken by the *Horus* system. Therefore, the *Horus* system should give optimal results. Figures 3 and 4 show the probability of error and average distance error (analytical and simulation results) respectively for the *Radar* and the *Horus* systems. The error bars represent the 95% confidence interval for the simulation experiments.<sup>2</sup> The figure shows that the analytical expressions obtained are consistent with the simulation results. Moreover, the *Horus* system performance is better than the *Radar* system as predicted by Theorem 2. The *Horus* system performance is optimal under the uniform distribution of user location.

The figure also shows that as the location determination system average more signal strength samples the error decreases. The more samples we average, the narrower the resulting distribution (lower variance), the less the overlap between the distribution at different locations and hence the less the error.


#### 4.3.2. Heterogeneous user profile distributions

This experiment study the case where a location determination system assumes that the user location follows a uniform distribution over all possible locations while the actual distribution is not.


Figures 5 and 6 show the probability of error and average distance error for profile 2. Figures 7 and 8 show the probability of error and average distance error for profile 3. The figures compares the *Radar* system, *Horus* system, and the optimal strategy which takes the user profile into account. The figures show that as the heterogeneity of the

---

<sup>2</sup>The analytical results are shown by lines to distinguish them from the simulation results (denoted by the subscript  $S$  in figures) which are shown as points with error bars.




(a) Horus System




(b) Radar System

Figure 3. Probability of error for the *Horus* and *Radar* systems under a uniform user profile (profile 1).




(a) Horus System




(b) Radar System


Figure 4. Expected distance error for the *Horus* and *Radar* systems under a uniform user profile (profile 1)



(a) Optimal Strategy




(b) Horus System




(c) Radar System


Figure 5. Probability of error under user profile 2.



(a) Optimal Strategy




(b) Horus System




(c) Radar System


Figure 6. Expected distance error under user profile 2.



(a) Optimal Strategy




(b) Horus System




(c) Radar System


Figure 7. Probability of error under user profile 3.



(a) Optimal Strategy



(b) Horus System



(c) Radar System

Figure 8. Expected distance error under user profile 3.

user profile increases (from profile 2 to profile 3), the performance of the location determination systems deviates from the optimal strategy. Figure 8 shows that the knowledge of the user profile is critical for environments where the number of access points deployed is limited and the heterogeneity of user profile is high. The figure shows that, for one access point, the optimal strategy gives an average distance error of about 2.25 feet while the strategies that does not take the user profile into account gives an average distance error of about 27 feet. However, as the number of access points increases, the difference between the performance of the location determination systems and the optimal strategy decreases. As the number of access points increases, the information the location determination system gets about the user location increases and dominates the information from the user profile. The *Horus* system maintains its superior performance over the *Radar* system.

## 5. Conclusions and Future Work

We have provided two novel contributions to the area of WLAN location determination systems. First, we presented an analysis method for studying the performance of WLAN location determination systems. The method can be applied to any of the WLAN location determination techniques and does not make any assumptions about the signal strength distributions at each location, independence of access points, nor the user profile. Second, we studied the effect of the user profile on the performance of the WLAN location determination systems.

We used the analytical method to obtain the optimal strategy for selecting the user location, which is not implemented by any of the current WLAN location determination systems. The optimal strategy must take into account the signal strength distributions at each location and the user profile. We also used analytical analysis to study the effect of averaging multiple signal strength vectors on performance. The results show that averaging multiple signal strength vectors reduces the variance of the resulting distribution and hence reduce the overlap between distributions. The less the overlap, the less the error.

We used simulation experiments to validate the analytical results and to study the effect of user profile on the performance of the location determination systems. The results show that incorporating the user profile in the location determination system can enhance the accuracy significantly when the available hardware is limited. However, with a reasonable number of access points that can be heard at each location, the performance of the location determination system is consistent under different user profiles.

For future work, the method can be extended to include other factors that affects the location determination process such as the user history profile (usually taken as the time average of the latest location estimates), and the correlation between samples from the same access points.

## References

- [1] <http://www.cs.umd.edu/users/moustafa/Downloads.html>.
- [2] P. Bahl and V. N. Padmanabhan. RADAR: An In-Building RF-based User Location and Tracking System. In *IEEE Infocom 2000*, volume 2, pages 775–784, March 2000.
- [3] P. Castro, P. Chiu, T. Kremenek, and R. Muntz. A Probabilistic Location Service for Wireless Network Environments. *Ubiquitous Computing 2001*, September 2001.
- [4] G. Chen and D. Kotz. A Survey of Context-Aware Mobile Computing Research. Technical Report Dartmouth Computer Science Technical Report TR2000-381, 2000.
- [5] P. Enge and P. Misra. Special issue on GPS: The Global Positioning System. *Proceedings of the IEEE*, pages 3–172, January 1999.
- [6] A. M. Ladd, K. Bekris, A. Rudys, G. Marceau, L. E. Kavraki, and D. S. Wallach. Robotics-Based Location Sensing using Wireless Ethernet. In *8th ACM MOBICOM*, Atlanta, GA, September 2002.
- [7] T. Roos, P. Myllymaki, H. Tirri, P. Misikangas, and J. Sievanen. A Probabilistic Approach to WLAN User Location Estimation. *International Journal of Wireless Information Networks*, 9(3), July 2002.
- [8] A. Smailagic, D. P. Siewiorek, J. Anhalt, D. Kogan, and Y. Wang. Location Sensing and Privacy in a Context Aware Computing Environment. *Pervasive Computing*, 2001.

- [9] W. Stallings. *Wireless Communications and Networks*. Prentice Hall, first edition, 2002.
- [10] The Institute of Electrical and Electronics Engineers, Inc. IEEE Standard 802.11 - Wireless LAN Medium Access Control (MAC) and Physical Layer (PHY) specifications. 1999.
- [11] M. Youssef and A. Agrawala. Small-Scale Compensation for WLAN Location Determination Systems. In *IEEE WCNC 2003*, March 2003.
- [12] M. Youssef, A. Agrawala, and A. U. Shankar. WLAN Location Determination via Clustering and Probability Distributions. In *IEEE PerCom 2003*, March 2003.
- [13] M. Youssef, A. Agrawala, A. U. Shankar, and S. H. Noh. A Probabilistic Clustering-Based Indoor Location Determination System. Technical Report UMIACS-TR 2002-30 and CS-TR 4350, University of Maryland, College Park, March 2002. <http://www.cs.umd.edu/Library/TRs/>.